



CB MINI

Citizens Band Radio

- Modulation Mode: FM /AM
- Noise Cancelling
- ECHO
- RF GAIN Adjustment
- Roger Beep
- DW
- SCAN
- TOT
- MUTE
- MIC GAIN Adjustment
- Backlight Brightness Adjustment
- ASQ / SQ



Multiple backlight color

CB MINI Citizens Band Radio

Main Functions

- Modulation Mode: FM /AM
- High / Low power select
- Noise Cancelling
- ASQ / SQ
- ECHO
- RF GAIN Adjustment
- MIC GAIN Adjustment
- DW
- SCAN
- TOT
- MUTE
- Roger Beep
- Multiple backlight color
- Backlight Brightness Adjustment

General		Receiver		Transmitter	
Modulation Mode	AM/FM	Sensitivity	Less than 1uV for 10dB(S+N)/N	Power Output	4 Watts FM/AM
Frequency Range	26.965-27.405MHz (Export 24.715MHz ~ 30.105MHz)	Image Rejection	70dB	Transmission interference	inferior to 4nW
Frequency Tolerance	±5.0ppm	Adjacent Channel Rejection	60dB	Frequency Response	300-3000Hz
Channels	40	IF Frequencies	1st 10.695MHz 2nd 455KHz	Modulated signal distortion	inferior to 5%
Dimensions	144.8*108.3*26.5mm		Less than 10dB change in audio	Output Impedance	50 ohms
Weight	335.3g	Automatic Gain Control(AGC)	Output for inputs from		
Operating Temperature Range	-20°C to +50°C		10 to 50000uV		
Current Drain	Transmit	2A MAX	Squelch	less than 1uV	
	Receive	Squelched 0.3A	Audio Output Power	2Watts	
	VOL Max	0.8A	Frequency Response	300-3000Hz	
Antenna Connector	UHF, SO-239				
Input Voltage	13.2V				

Standard Accessories



Optional Accessories



Quanzhou TYT Electronics Co., Ltd.
 Address: Block 39-1, Optoelectronics-information industry
 base, Nan'an, Quanzhou, Fujian, China
 Website: www.tyt888.com
 Nationwide Toll Free No.: 400-699-8858

