



■ d.-No.: 12691

MULTICHANNEL CB-RADIO FOR EUROPE

> AE 6891

Detachable front section with
bracket for dashboard mounting



Specifications

- ▶ UE: 40 UK frequencies 4 Watt, FM
- ▶ dE: German frequencies 80 FM 4 Watt, 40 AM 1 Watt
- ▶ E: Italy, Spain, Europe (new) 40 channels, 4 Watt AM/FM
- ▶ EU: Europe (old) 40 channels AM/FM, 1 Watt AM/4 Watt FM
- ▶ CE: 40 channels FM 4 Watt only
- ▶ Po: 40 channels AM 4 Watt/FM 4 Watt for Poland with Offset 5 kHz
- ▶ Adaptable to the new EU norm with a plug-in jumper
- ▶ 6 Country switching by software operation
- ▶ Automatic squelch ASQ and manual squelch
- ▶ Channels selectable by rotary and UP/DN keys on the microphone
- ▶ Illuminated microphone
- ▶ Big graphic LC display (55 x 24 mm) with dimmer for channel, s-meter, power-meter, frequency and status icons
- ▶ Channel/frequency display selectable
- ▶ Audio tone filter (TON)
- ▶ Mic sensitivity High/Low selectable
- ▶ RF gain switch for local/DX operation (LOC)
- ▶ Roger Beep for AM and FM
- ▶ Build in NB (noise blanker) circuit
- ▶ External s-meter socket (2.5 mm)
- ▶ Die cast back panel with heat sink (for longer QSOs)
- ▶ AM-FM switch
- ▶ 4 memory channels
- ▶ Scan functions for all channels (SC) or special Channel dual watch (DW)
- ▶ Channel 9 direct key
- ▶ Key tones and Roger Beep selectable for AM and FM
- ▶ Flash-EEPROM memory for last setting
- ▶ Remote cable length about 2 meters

Alan Electronics GmbH

Daimlerstraße 1 k · D-63303 Dreieich
Tel.: +49(0)6103-9 48 10 · Fax: +49(0)6103-94 81 60
www.alan-electronics.de · info@alan-electronics.de

Dovenkamp 11 · D-22952 Lütjensee
Tel.: +49 (0)4154-84 90 · Fax: +49 (0)4154-84 91 00
www.lkw-cb.de · kontakt@alan-electronics.de